

F-2YA2Y, F-2YC2Y, F-2YJA2Y

The cores are stranded in star quads. Two opposite cores of a quad build a talking circuit.

core identification in a quad :

circuit 1	a-core ... natural b-core ... red
circuit 2	c-core ... green d-core ... blue

One quad is marked as a tracer quad with a black a-core in each layer.

Number of star quads in each layer

number of		number of star quads in each layer					
quads	pairs	1	2	3	4	5	6
25	50	3	8	14			
50	100	4	10	15	21		
75	150	3	9	15	21	27	
100	200	2	8	14	20	25	31